

# Fluke 8808A Digital Multimeter

## Extended Specifications

### Making measurements is as simple as pushing a button

The Fluke 8808A 5.5 digit multimeter has a broad range of functions, measuring volts, ohms and amps with a basic V dc accuracy of 0.01 %. It is remarkably easy to use, even by unskilled operators, because it makes the measurements you perform most often extremely easy and fast to do.

Six setup buttons on the 8808A front panel operate like a car radio's station presets. Simply set up the meter for a common measurement, then press shift followed by a setup button (S1 to S6) to save the setup. Now each time you perform that measurement, you simply press the appropriate setup key. It's that easy!

The setup buttons eliminate the need to follow complex work instruction sheets. Operators no longer need to press multiple buttons to set up a measurement function and range, test limits, or enter other parameters to make a measurement.

### Eliminate production mistakes

The Fluke 8808A 5.5 digit multimeter dependably performs the most common measurements required by today's applications.



### Features at a glance

- 5.5 digit resolution
- Basic V dc accuracy of 0.01 %
- Dual display
- Dedicated dc leakage current measurement
- 2x4 ohms 4-wire measurement technique
- Six dedicated buttons for fast access to instrument setups
- Hi.Lo limit compare for Pass/Fail testing
- Fluke 45 remote command emulation

Whether you are performing functional tests or making critical measurements on test points, using the limit compare mode with pass/fail indicators eliminates production mistakes, especially those where results are "on the edge."

The 8808A display has built-in enunciators that clearly show the operator whether a test passes or fails. The pass/fail indicators take the guesswork out of testing: the result is either within limits or it's out.

## 8808A Specifications

### Voltage

100V Setting .....	90 V to 110 V
120V Setting .....	108 V to 132 V
220V Setting .....	198 V to 242 V
240V Setting .....	216 V to 264 V
Frequency .....	47 Hz to 440 Hz.
Power Consumption .....	15 VA peak (10 W average)

### Dimensions

Height .....	88 mm (3.46 in)
Width .....	217 mm (8.56 in)
Depth .....	297 mm (11.7 in)
Weight .....	2.1 kg (4.6 lbs)

### Display

Vacuum Fluorescent Display, segment

### Environment

#### Temperature

Operating .....	0 °C to 50 °C
Storage .....	-40 °C to 70 °C
Warm Up .....	½ hour to full uncertainty specifications

#### Relative Humidity (non-condensing)

Operating .....	Uncontrolled (< 10°C)
	<90 % (10 °C to 30 °C)
	<75 % (30 °C to 40 °C)
	<45 % (40 °C to 50 °C)
Storage .....	-40 °C to 70 °C <95 %

#### Altitude

Operating .....	2,000 Meters
Storage .....	12,000 Meters

**Vibration** .....

Complies with MIL-PRF-28800F Class 3

### Safety

Complies with IEC 61010-1:2001, ANSI/ISA 61010-1 (S82.02.01):2004, UL 61010-1:2004, CAN/CSA C22.2 No. 61010.1:2004, CAT I 1000V/CAT II 600 V.

### EMC

Designed to comply with IEC 61326-1:1997+A1:1998+A2:2000

### Triggering

Trigger Delay .....	400 ms
External Trigger Delay .....	<2 ms
External Trigger Jitter .....	<1 ms
Trigger Input .....	TTL Levels
Trigger Output .....	5 V max

### Math Functions

Min/max, relative, hold, compare and dB functions.

### Electrical

Input Protection .....	1000 V all ranges
Overrange .....	10 % on the largest ranges of all functions except continuity and diode test

### Remote Interfaces

RS-232C

### Warranty

One year

# Electrical Specifications

Accuracy specifications are valid for 5-1/2 digit mode and after at least a half-hour warm-up.

## DC Voltage Specifications

- Maximum Input** ..... 1000 V on any range.
- Common Mode Rejection** ..... 120 dB at 50 or 60 Hz ±0.1% (1 kΩ unbalance)
- Normal Mode Rejection** ..... 80 dB at Slow Rate
- A/D Nonlinearity** ..... 15 ppm of range
- Input Bias Current** ..... <30 pA at 25 °C
- Settling Considerations** ..... Measurement settling times are affected by source impedance, cable dielectric characteristics, and input signal changes

### Input Characteristics

Range	Full-Scale (5-1/2 Digits)	Resolution			Input Impedance
		Slow	Medium	Fast	
200 mV	199.999 mV	1 μV	10 μV	10 μV	>10 G <sup>[1]</sup>
2 V	1.99999 V	10 μV	100 μV	100 μV	>10 G <sup>[1]</sup>
20 V	19.9999 V	100 μV	1000 μV	1000 μV	10 M ± 1 %
200 V	199.999 V	1 mV	10 mV	10 mV	10 M ± 1 %
1000 V	1000.00 V	10 mV	100 mV	100 mV	10 M ± 1 %

Notes:  
 [1] At some dual display measurements, the input impedance of 200 mV and 2 V ranges may be changed to 10 M .

### Accuracy

Range	Accuracy <sup>[1]</sup>		Temperature Coefficient/°C Outside 18 – 28 °C
	90 days	1 year	
	23 °C ± 5 °C		
200 mV	0.01 + 0.003	0.015 + 0.004	0.0015 + 0.0005
2 V	0.01 + 0.002	0.015 + 0.003	0.001 + 0.0005
20 V	0.01 + 0.003	0.015 + 0.004	0.0020 + 0.0005
200 V	0.01 + 0.002	0.015 + 0.003	0.0015 + 0.0005
1000 V	0.01 + 0.002	0.015 + 0.003	0.0015 + 0.0005

Notes:  
 [1] Accuracy given as ± (% of reading + % of range)

### AC Voltage Specifications

AC Voltage specifications are for ac sinewave signals >5 % of range. For inputs from 1 % to 5 % of range and <50 kHz, add an additional error of 0.1 % of range, and for 50kHz to 100 kHz, add 0.13 % of range.

**Maximum Input** .....750 V rms or 1000 V peak or  $8 \times 10^7$  Volts-Hertz product  
**Measurement Method** .....AC-coupled true-rms. Measures the ac component of input with up to 1000 V dc bias on any range.

**AC Filter Bandwidth:**

Slow .....20 Hz – 100 kHz

**Common Mode Rejection** .....60 dB at 50 Hz or 60 Hz (1 k unbalance)

**Maximum Crest Factor** .....3:1 at Full Scale

**Additional Crest Factor Errors (<100 Hz)** .....Crest Factor 1-2, 0.05 % of full scale  
 Crest Factor 2-3, 0.2 % of full scale

**Input Characteristics**

Range	Full-Scale (5-1/2 Digits)	Resolution			Input Impedance
		Slow	Medium	Fast	
200 mV	199.999 mV	1 uV	10 uV	10 uV	1 M $\pm 2$ % shunted by <100 pf
2 V	1.99999 V	10 uV	100 uV	100 uV	
20 V	19.9999 V	100 uV	1000 uV	1000 uV	
200 V	199.999 V	1 mV	10 mV	10 mV	
750 V	750.00 V	10 mV	100 mV	100 mV	

**Accuracy**

Range	Frequency	Accuracy <sup>[1]</sup>		Temperature Coefficient/°C Outside 18 – 28 °C
		90 days	1 year	
		23 °C $\pm$ 5 °C	23 °C $\pm$ 5 °C	
200 mV	20 Hz – 45Hz	0.8 + 0.05	0.9 + 0.05	0.01 + 0.005
	45 Hz – 20 kHz	0.15 + 0.05	0.2 + 0.05	0.01 + 0.005
	20 kHz – 50 kHz	0.3 + 0.05	0.35 + 0.05	0.01 + 0.005
2 V	50 kHz – 100 kHz	0.8 + 0.05	0.9 + 0.05	0.05 + 0.01
	20 Hz – 45Hz	0.8 + 0.05	0.9 + 0.05	0.01 + 0.005
	45 Hz – 20 kHz	0.15 + 0.05	0.2 + 0.05	0.01 + 0.005
20 V	20 kHz – 50 kHz	0.3 + 0.05	0.35 + 0.05	0.01 + 0.005
	50 kHz – 100 kHz	0.8 + 0.05	0.9 + 0.05	0.05 + 0.01
	20 Hz – 45 Hz	0.8 + 0.05	0.9 + 0.05	0.01 + 0.005
200 V	45 Hz – 20 kHz	0.15 + 0.05	0.2 + 0.05	0.01 + 0.005
	20 kHz – 50 kHz	0.3 + 0.05	0.35 + 0.05	0.01 + 0.005
	50 kHz – 100 kHz	0.8 + 0.05	0.9 + 0.05	0.05 + 0.01
750 V	20 Hz – 45Hz	0.8 + 0.05	0.9 + 0.05	0.01 + 0.005
	45 Hz – 20 kHz	0.15 + 0.05	0.2 + 0.05	0.01 + 0.005
	20 kHz – 50 kHz	0.3 + 0.05	0.35 + 0.05	0.01 + 0.005
	50 kHz – 100 kHz	0.8 + 0.05	0.9 + 0.05	0.05 + 0.01

Notes:

[1] Accuracy given as  $\pm$  (% of reading + % of range)

**Resistance**

Specifications are for 4-wire resistance function, or 2-wire resistance with REL. If REL is not used, add 0.2 Ω for 2-wire resistance plus lead resistance.

**Measurement Method** .....Current source referenced to LO input

**Max Lead Resistance (4-wire ohms)**.....10 % of range per lead for 200 Ω, 2 k Ω ranges. 1 k Ω per lead on all other ranges.

**Input Protection** .....1000 V on all ranges

**Input Characteristics**

Range	Full-Scale (5-1/2 Digits)	Resolution			Current Source
		Slow	Medium	Fast	
200	199.999	0.001	0.01	0.01	0.8 mA
2 k	1.99999 k	0.01	0.1	0.1	0.8 mA
20 k	19.9999 k	0.1	1	1	0.08 mA
200 k	199.999 k	1	10	10	0.008 mA
2 M	1.99999 M	10	100	100	0.9 μA
20 M	19.9999 M	100	1 k	1 k	0.16 μA
100 M	100.000 M	1 k	10 k	10 k	0.16 μA    10 M

**Accuracy**

Range	Accuracy <sup>[1]</sup>		Temperature Coefficient/°C Outside 18 – 28 °C
	90 days	1 year	
	23 °C ± 5 °C	23 °C ± 5 °C	
200	0.02 + 0.004	0.03 + 0.004	0.003 + 0.0006
2 k	0.015 + 0.002	0.02 + 0.003	0.003 + 0.0005
20 k	0.015 + 0.002	0.02 + 0.003	0.003 + 0.0005
200 k	0.015 + 0.002	0.02 + 0.003	0.003 + 0.0005
2 M	0.03 + 0.003	0.04 + 0.004	0.004 + 0.0005
20 M	0.2 + 0.003	0.25 + 0.003	0.01 + 0.0005
100 M	1.5 + 0.004	1.75 + 0.004	0.2 + 0.0005

Notes:

[1] Accuracy given as ± (% of reading + % of range)

**DC Current**

**Input Protection** .....Tool accessible 11 A / 1000 V and 440 mA / 1000 V fuses.

**Shunt Resistance** .....0.01 Ω for 2 A and 10 A ranges

1 Ω for 20 mA and 200 mA

Burden voltage < 1 mV for 200 μA and 2 mA range.

**Input Characteristics**

Range	Full-Scale (5-1/2 Digits)	Resolution			Burden Voltage
		Slow	Medium	Fast	
200 μA	199.999 μA	0.001 μA	0.01 μA	0.01 μA	<1 mV
2 mA	1999.99 μA	0.01 μA	0.1 μA	0.1 μA	<1 mV
20 mA	19.9999 mA	0.1 μA	1 μA	1 μA	<0.05 V
200 mA	199.999 mA	1 μA	10 μA	10 μA	<0.5 V
2 A	1.99999 A	10 μA	100 μA	100 μA	<0.1 V
10 A	10.0000 A	100 μA	1 mA	1 mA	<0.5 V



**Frequency**

**Gate Time**..... 131 ms  
**Measurement Method** .....AC-coupled input using the ac voltage measurement function.  
**Settling Considerations**.....When measuring frequency after a dc offset voltage change, errors may occur. For the most accurate measurement, wait up to 1 second to allow input blocking RC time constant to settle.  
**Measurement Considerations** .....To minimize measurement errors, shield inputs from external noise when measuring low voltage, low frequency signals.

**Accuracy**

Range	Frequency	Accuracy		Temperature Coefficient/°C Outside 18 – 28 °C
		90 days	1 year	
		23 °C ± 5 °C	23 °C ± 5 °C	
100 mV to 750 V <sup>[1,2]</sup>	20 Hz – 2 kHz	0.01 + 0.002	0.01 + 0.003	0.002 + 0.001
	2 kHz – 20 kHz	0.01 + 0.002	0.01 + 0.003	0.002 + 0.001
	20 kHz – 200 kHz	0.01 + 0.002	0.01 + 0.003	0.002 + 0.001
	200 kHz – 1 MHz	0.01 + 0.004	0.01 + 0.006	0.002 + 0.002

Notes:  
 [1] Input > 100 mV  
 [2] Limited to 8\* 10<sup>7</sup> V Hz

**Continuity**

**Continuity Threshold**.....20  
**Test Currents** ..... 1 mA  
**Response Time** ..... 100 samples/sec with audible tone  
**Rate**..... Fast  
**Maximum Reading**.....199.99  
**Resolution**.....0.01

**Diode Test**

**Response Time**.....100 samples/sec with audible tone  
**Rate**.....Fast  
**Maximum Reading**.....1.9999 V  
**Resolution**.....0.1 mV

## Ordering information

Models	Description
8808A 120V	5.5 Digit Multimeter
8808A 220V	5.5 Digit Multimeter
8808A 100V	5.5 Digit Multimeter
8808A 240V	5.5 Digit Multimeter

### 8808A/SU includes

8808A package plus, FlukeView Forms basic software, USB to RS-232 interface adapter cable.

8808A/SU 120V	5.5 Digit Multimeter, SW USB Cable Kit
8808A/SU 220V	5.5 Digit Multimeter, SW USB Cable Kit
8808A/SU 100V	5.5 Digit Multimeter, SW USB Cable Kit
8808A/SU 240V	5.5 Digit Multimeter, SW USB Cable Kit

### 8808A includes

Meter, TL71 test leads, line cord, spare line fuse, statement of cal practices, WEEE information sheet, Warranty statement, Getting Started guide (English, French, German, Spanish, Italian, Simplified Chinese, Japanese), CD Rom with user manual (English).



**S J ELECTRONICS**  
POWER • TEST & MEASUREMENT

**0800 583 44 55**

Tel: +44 1536 416 200

Fax: 0800 583 55 66

sales@sjelectronics.co.uk

www.sjelectronics.co.uk

**Fluke.** Keeping your world  
up and running.®

#### Fluke Corporation

PO Box 9090, Everett, WA USA 98206

#### Fluke Europe B.V.

PO Box 1186, 5602 BD  
Eindhoven, The Netherlands

#### For more information call:

In the U.S.A. (800) 443-5853 or

Fax (425) 446-5116

In Europe/M-East/Africa +31 (0) 40 2675 200 or

Fax +31 (0) 40 2675 222

In Canada (800)-36-FLUKE or

Fax (905) 890-6866

From other countries +1 (425) 446-5500 or

Fax +1 (425) 446-5116

Web access: <http://www.fluke.com>

©2007 Fluke Corporation.

Specifications subject to change without notice.

Printed in U.S.A. 9/2007 3093965 D-EN-N Rev B

Pub\_ID: 11288-eng Rev 01